

# CUSTOMER SERVICE BULLETIN

## Radio Shack® CUSTOMER SERVICE BULLETIN

400 Atrium—One Tandy Center, Fort Worth, Texas 76102

Bulletin No.	1506-02
Description	CASSETTE PORTFOLIO
Model	Model III
Stock No.	26-1506 Version 1.0
Date	March 31, 1982
Page 1 of	1

### Problem

Sell calculations in option program are reversed.

### Solution

The problem is corrected by following the steps listed below.

1. In BASIC, CLOAD the Option tape.
2. Make the following corrections:

CHANGES (Retype the line or refer to the Edit section of the owners manual)

Old Line: 340 FORI=1TONO:O6#(I)=(O5#(I)\*O(I,2)\*100)-O4#(I):NEXT

New Line: 340 FORI=1TONO:GOSUB800:NEXT

ADD THESE LINES:

```
800 CV#=O5#(I)*O(I,2)*100:REM CURRENT VALUE
810 OV#=O(I,0)*0(I,2)*100:REM OPTION VALUE
820 OC#=O4#(I):REM OPTION COST
830 IFO3$(I)="B"THENGL#=CV#-OV#-OC#ELSEGL#=OV#+OC#-CV#
840 O6#(I)=GL#:RETURN
```

3. Type CSAVE to save the changes in the tape program.