

Radio Shack® CUSTOMER SERVICE BULLETIN

400 Atrium—One Tandy Center, Fort Worth, Texas 76102

Bulletin No. 1554-21

Description ACCOUNTS PAYABLE

Model	Model III
-------	-----------

Stock No. 26-1554 Ver. 03.01.02

Date April 15, 1983

Page 1 of 1

Problem

The program REPORTS will produce phantom line feeds when the dashed total line is printed if an 80 column printer is used.

**** THE FOLLOWING CHANGES ARE REQUIRED FOR USE WITH 80 COLUMN PRINTERS! ****

Solution

1. Backup the diskette(s) and make the changes on the Backup copy of the program.
2. In BASIC load the program by typing LOAD"REPORTS".
3. Make the following corrections:

CHANGES (Retype the line or refer to the Edit section of the owners manual)

```
Old Line: 7 CLEAR1500:DEFDBLA-C,T:DEFINTD-S,U-Z:DIMW,W$,DF,U1$(128),U(22):
L2$=CHR$(31):L3$=STRING$(80,61):L4$=STRING$(80,45):F1$="$ $#####"
##":F2$="$ $#####"##":S$=STRING$(10,45)+"  "
```

```
New Line: 7 CLEAR1500:DEFDBLA-C,T:DEFINTD-S,U-Z:DIMW,W$,DF,U1$(128),U(22):
L2$=CHR$(31):L3$=STRING$(80,61):L4$=STRING$(80,45):F1$="$ $#####.
##":F2$="$ $#####. ##":S$""+STRING$(10,45)
```

Old Line: 145 T0=T0+C4:T1=T1+C5:T2=T2+C6:T3=T3+C7: IFVL\$="F" THEN LPRINT TAB
(30)SSSSSSSS

```
New Line: 145 T0=T0+C4:T1=T1+C5:T2=T2+C6:T3=T3+C7: IFVL$="F" THEN LPRINT TAB
(27) SSSSSSSS
```

4. Type `SAVE"REPORTS"` to save the changes in the program.
5. At `TRSDOS READY`, make a backup copy of the corrected diskette.