

CUSTOMER SERVICE BULLETIN

Radio Shack® CUSTOMER SERVICE BULLETIN

400 Atrium—One Tandy Center, Fort Worth, Texas 76102

| | |
|---------------------|-----------------------|
| Bulletin No. | 1558-05 |
| Description | BUSINESS MAILING LIST |
| Model | Model III |
| Stock No. | 26-1558 Ver. 03.00.00 |
| Date | March 7, 1983 |
| Page 1 of | 1 |

Problem

There are only 9 spaces allowed for Zip Code. This does not allow room for a hyphenation mark.

* * THE FOLLOWING CHANGE IS OPTIONAL! * *

Solution

This patch will add a hyphen only under the following conditions:

- (1) The Zip Code fills the field (i.e., 9 digits).
- (2) The Zip Code begins with numeric, and not alpha.

Example: 123456789 will print as 12345-6789
A12345678 or 12345678 will not print the hyphen.
12345ABCD will print as 12345-ABCD

1. Backup the diskette(s) and make the changes on the Backup copy of the program.
2. In BASIC load the program by typing LOAD"MLS".
3. Make the following corrections:

CHANGES (Refer to the Edit section of the owners manual)

ADD NEW Line: 2475 IFVAL(E6\$)>0ANDINSTR(E6\$," ")<1THENE6\$=MID\$(E6\$,1,5)+"-"
+MID\$(E6\$,6)

4. Type SAVE"MLS" to save the changes in the program.
5. At TRSDOS READY, make a backup copy of the corrected diskette.