

CUSTOMER SERVICE BULLETIN

Radio Shack® CUSTOMER SERVICE BULLETIN

400 Atrium—One Tandy Center, Fort Worth, Texas 76102

Bulletin No.	1568-04 (CORRECTION 2)
Description	Medical Office Systems
Model	Model I/III
Stock No.	26-1568 Version 1.0
Date	Feb. 25, 1982
Page 1 of	3

Problem

Medical Office System contains a bug which may cause problems if more than three patient data files are used.

* * THIS FIX IS REQUIRED! * *

Solution

** Changes to MOS are somewhat critical, the following process should be followed closely. USE THE FOLLOWING FIX ONLY ONCE. If the problem is not solved with ONE application of the fix, further applications will cause loss of data! **

1. In BASIC, LOAD"ALPHASOR".

2. Type these lines as shown.

```
1240 FZ=INT((AC-1)/Z1):IFFZ<>FOTHENFO=FZ:CLOSE3:
    FM$="PDATA"+CHR$(48+FO)+" :3":NU=3:GOSUB4000 :CLS
```

```
1250 LR=AC-FO*Z1:PR=INT((LR-1)/2)+1:SR=LR-2*INT((LR-1)/2)-1
```

3. SAVE"ALPHASOR"

4. In BASIC, LOAD"MENU".

5. Add these lines as shown.

```
120 FZ=INT((AC-1)/Z1):IFFZ<>FOTHENFO=FZ:CLOSE3:
    FM$="PDATA"+CHR$(48+FO)+" :3":NU=3:GOSUB4000
```

```
140 LR=AC-FO*Z1:PR=INT((LR-1)/2)+1:SR=LR-2*INT((LR-1)/2)-1
```

CUSTOMER SERVICE BULLETIN

Subject 1568-04 Medical Office Systems (Correction 2) Page 2 Of 3

```
1400 DEF FNA(X)=PEEK(X)+PEEK(X+1)*256:E=FNA(&H40A4)
1410 S=FNA(E):IF FNA(S+2)<1000 THEN E=S:GOTO 1410
1420 PRINT"TP=TP+S-FNA(&H40A4)"IN LINE 1110:END
```

5. TYPE 'GOTO1400

(The computer will pause and print "TP=TP+NNNN IN LINE 1110". The NNNN will be a number.)

6. TYPE 'LIST1110

(If the number after TP=TP+... does not match the computer generated number, the line must be edited to contain the new value.)

7. TYPE 'EDIT1170

Line 1170 should look like this:

```
1170 DATAMONSORT,PRINT STATEMENTS,BLLPRT,SET UP SYSTEM DISKS,INIT,16922,
      16923,16924,1390,4170,3,16452,16453,16454,660,3960,6
```

(If the numbers under the word 'PRINT' are not 1390,4170 edit them to conform to the new line 1170. There are no other changes in the line.)

8. TYPE 'SAVE"MENU"

** FORMAT A NEW DATA DISK FOR EACH PATIENT DATA DISK.

Type in this PROGRAM:

```
10 CLEAR2000:CLS:AC=1:FO=-1:B2=-1
20 IFPEEK(293)=73 THEN Z1=1390 ELSE Z1=660
30 D$(1)="OLD":D$(2)="NEW"
40 CLS:INPUT"WHAT IS YOUR PASSWORD? (PRESS <ENTER> IF NONE)";PW$
50 IFPW$="" THEN NPW$="PASSWORD"
60 PW$="."+PW$
70 IFFO<>INT(AC/(Z1+1)) THEN CLOSE1:FO=INT(AC/(Z1+1)):D=1:DN=FO+1:
  GOSUB140:OPEN"R",1,"PDATA"+CHR$(FO+48)+PW$+"":1"
80 PRINT@339,AC
90 IR=AC-FO*Z1+1:PR=INT((IR-1)/2)+1:SR=IR-2*INT((IR-1)/2)-1
100 FIELD1,SR*127ASAL$,127ASAS$:GET1,PR
110 B1=INT((AC-1)/Z1):IFB1<>B2 THEN B2=B1:CLOSE2:FM$="PDATA"+CHR$(48+B1)+":
  2":D=2:DN=B2+1:GOSUB140:OPEN"R",2,"PDATA"+CHR$(48+B1)+PW$+"":2"
120 B=AC-B1*Z1:B3=INT((B-1)/2)+1:B4=B-2*INT((B-1)/2)-1
130 FIELD2,B4*127ASB1$,127ASB$:LSETB$=A$:PUT2,B3:AC=AC+1:GOTO70
```

CUSTOMER SERVICE BULLETIN

Subject 1568-04 Medical Office Systems (Correction 2) **Page** 3 **Of** 3

```
140 IFAC>1THENMS$="NEXT"  
150 CLS:PRINT"PUT "D$(D)" PATIENT DATA DISK"DN"IN DRIVE"D  
160 PRINT:PRINT"PRESS <ENTER> WHEN READY, OR <@> TO END"  
170 W$=INKEY$:IFW$=""THEN170  
180 IFW$=CHR$(13)THENCLS:PRINT@320,"WORKING ON RECORD #";:RETURN  
190 IFW$="@"THENCLOSE:ENDELSE170
```

FOLLOW THE PROMPTS, INSERTING OLD AND NEW DISKS AS REQUESTED.
THESE NEW DISKS WILL BE USED WITH THE MODIFIED MOS DISK.
DO NOT ATTEMPT TO USE THE OLD PATIENT DATA DISKS WITH THE MODIFIED PROGRAM.