

CUSTOMER SERVICE BULLETIN

Radio Shack® CUSTOMER SERVICE BULLETIN

400 Atrium—One Tandy Center, Fort Worth, Texas 76102

Bulletin No.	3320-01
Description	CARD GAMES
Model	Color
Stock No.	26-3320 Ver. 01.00.00
Date	June 28, 1983
Page 1 of	2

Problem

When all cards are face up in SOLITAIRE, using "W" for a quick finish causes the system to lock up.

* * THE FOLLOWING CHANGES ARE REQUIRED! * *

Solution

1. Using a clean blank tape, type CSAVE"SOLITAIRE" to save the changes in the program.
2. Place the SOLITAIRE Program in the cassette recorder and in BASIC load the program by typing CLOAD"SOLITAIRE".
3. Make the following corrections:

CHANGES (Retype the line or refer to the Edit section of the owners manual)

Old Line: 10 GOSUB60000:CKS:ORUBT@12,"SOLITAIRE":PCLEAR4:PMODE4:PCLS:CLEAR
350:FORI=480TO511:READX:POKEI,X:NEXT:DIMC(51),B(3,4),T(3,4),S(17,
6),N\$(12),S\$(3),L(6),U(1,1),F(3),R(11),D(23):X1=2:Y1=1:XX=226:YY
=154:X3=40:Y3=3:F=-1:PRINT@41,"BY: JAMES GARON

New Line: 10 GOSUB60000:CLS:PRINT@12,"SOLITAIRE":PCLEAR4:PMODE4:PCLS:CLEAR
300:FORI=480TO514:READX:POKEI,X:NEXT:DIMC(51),B(3,4),T(3,4),S(17,
6),N\$(12),S\$(3),L(6),U(1,1),F(3),R(11),D(23):X1=2:Y1=1:XX=226:YY
=154:X3=40:Y3=3:F=-1:PRINT@41,"BY: JAMES GARON

Old Line: 2000 POKE485,10:POKE486,32:EXEC480:Y=5:FOR S=0TO3:X=80+46*S:FORV=
F(S)+1+(F(S)=12)TO12:GOSUB1000:NEXT:PLAYF\$:F(S)=12:NEXT:POKE485,
6:POKE486,0

CUSTOMER SERVICE BULLETIN

Subject 3320-01 CARD GAMES Page 2 Of 2

New Line: 2000 POKE488,4:POKE489,64:POKE494,158:EXEC480:Y=5:FORS=0TO3:
X=80+46*S:FORV=F(S)+1+(F(S)=12)TO12:GOSUB1000:NEXT:PLAYF\$:F(S)=
12:NEXT:POKE488,0:POKE489,0:POKE494,192

Old Line: 5000 DATA16,142,,31,150,188,95,31,3,142,0,192,198,31,166,65,167
,192,90,38,249,51,65,48,31,38,241,49,63,38,229,57

New Line: 5000 DATA16,142,,31,150,188,95,195,,,31,3,142,0,192,198,31,166
,65,167,192,90,38,249,51,65,48,31,38,241,49,63,38,226,57