

# CUSTOMER SERVICE BULLETIN

## Radio Shack® CUSTOMER SERVICE BULLETIN

400 Atrium—One Tandy Center, Fort Worth, Texas 76102

Bulletin No.	3526-01
Description	ENG. MATH II
Model	PC-2
Stock No.	26-3526 Version 01.00.00
Date	April 17, 1984
Page 1 of	1

### Problem

Program VECTOR errs in rectangular polar conversion.

\* \* THE FOLLOWING CHANGE IS REQUIRED! \* \*

### Solution

1. In BASIC load the program by typing CLOAD"VECTOR".
2. Make the following corrections.

Old Line: 620:Q=1:G=A:H=B:I=C:N=X:O=Y:P=Z:GOSUB 40:A=X:B=Y:C=Z:M=-M+1:GOSUB 60:M=R

New Line: 620:Q=1:G=A:H=B:I=C:N=X:O=Y:P=Z:GOSUB 40:IF MLET A=X:B=Y:C=Z

Add New Line: 627:M=-M+1:GOSUB 60:M=R

3. Type CSAVE "VECTOR" to save the changes in the program to a new tape.
4. Make a backup of the corrected tape.

After the changes from this bulletin have been made, the Version number will be 01.00.01. Please make the necessary entry in your Version Log.