

# CUSTOMER SERVICE BULLETIN

## Radio Shack® CUSTOMER SERVICE BULLETIN

400 Atrium—One Tandy Center, Fort Worth, Texas 76102

<b>Bulletin No.</b>	4531-07
<b>Description</b>	SCRIPSIT 2.0
<b>Model</b>	Model II
<b>Stock No.</b>	26-4531 Version 2.0
<b>Date</b>	May 28, 1982
<b>Page 1 of</b>	2

### Problem

Below is a list of 4 problems that are encountered in the repagination module of Scripsit 2.0. These patches must be applied in sequence.

### Solution

When repaginating a document and reformatting it, locked blocks are sometimes changed. The margins will not be adjusted, but tabs will be refigured, leading to strange results.

To prevent this from happening, apply the following patches. The date at the bottom of the STARTUP screen must be 02/23/1982 before you apply these patches; if it is not, obtain and apply all previous patches.

```
PATCH SCRIPSIT/SYS R=59 B=142 F=20BBF1FD361400 C=FD36140020B7F1
PATCH SCRIPSIT/SYS R=61 B=241 F=01 C=02
```

Sometimes user defined print codes would be split by the "wraparound" feature of the system. This caused confusion in recognizing them as print codes and/or translating them properly. The following patches correct the problem:

```
PATCH SCRIPSIT/SYS R=157 B=220 F=D64147 C=CD58D6
PATCH SCRIPSIT A=9F67 F=E1FE07 C=C360D6
PATCH SCRIPSIT A=D658 F=00000000000000000000 C=E67FD64147C9E17EFE07
PATCH SCRIPSIT A=D664 F=000000 C=C36A9F
```

# CUSTOMER SERVICE BULLETIN

Subject SCRIPSIT 2.0 4531-07 Page 2 Of 2

The Merge routine was failing to set up the proper data for alignment tabs. This sometimes caused the aligned text to print in the wrong column when merging. The following patches will correct the problem:

```
PATCH SCRIPSIT/SYS R=139 B=175 F=32FDDA C=CD4ED6
PATCH SCRIPSIT A=D64E F=00000000000000000000 C=32FDDAFD7E163223FFC9
```

When using the SCRIPSIT backup utility the user was not prompted if the destination diskette contained data. When doing a backup to the same drive other than drive 0, the source diskette would be formatted. The following patches will correct the problem:

```
PATCH SCRIPSIT/SYS R=37 B=147 F=32EDE2 C=C36BD6
PATCH SCRIPSIT A=D66B F=00000000000000000000 C=32EDE26F3A10E3BD200D
PATCH SCRIPSIT A=D675 F=00000000000000000000 C=FE30280921202022F0E2
PATCH SCRIPSIT A=D67F F=00000000000000000000 C=22F2E2C340E4
```

After applying these patches, apply the following to change the date in the STARTUP screen:

```
PATCH STARTUP A=E40E F=B0B2AFB2B3 C=B0B5AFB2B0
```