

Radio Shack® CUSTOMER SERVICE BULLETIN

Bulletin No.	<u>4531-Ø7</u>
Description	<u>SCRIPSIT 2.Ø</u>
Model	<u>Model II</u>
Stock No.	<u>26-4531 Version 2.Ø</u>
Date	<u>May 28, 1982</u>
Page 1 of	<u>2</u>

```
PATCH SCRIPSIT/SYS R=157 B=220 F=D64147 C=CD58D6
PATCH SCRIPSIT A=9F67 F=ElFE07 C=C360D6
PATCH SCRIPSIT A=D658 F=000000000000000000000000 C=E67FD64147C9E17EFE07
PATCH SCRIPSIT A=D664 F=000000 C=C36A9F
```

CUSTOMER SERVICE BULLETIN

Subject SCRIPSIT 2.0 4531-07 Page 2 Of 2

The Merge routine was failing to set up the proper data for alignment tabs. This sometimes caused the aligned text to print in the wrong column when merging. The following patches will correct the problem:

```
PATCH SCRIPSIT/SYS R=139 B=175 F=32FDDA C=CD4ED6
PATCH SCRIPSIT A=D64E F=000000000000000000000000 C=32FDDAFD7E163223FFC9
```

When using the SCRIPSIT backup utility the user was not prompted if the destination diskette contained data. When doing a backup to the same drive other than drive 0, the source diskette would be formatted. The following patches will correct the problem:

```
PATCH SCRIPSIT/SYS R=37 B=147 F=32EDE2 C=C36BD6
PATCH SCRIPSIT A=D66B F=000000000000000000000000 C=32EDE26F3A10E3BD200D
PATCH SCRIPSIT A=D675 F=000000000000000000000000 C=FE30280921202022F0E2
PATCH SCRIPSIT A=D67F F=000000000000000000000000 C=22F2E2C340E4
```

After applying these patches, apply the following to change the date in the STARTUP screen:

```
PATCH STARTUP A=E40E F=B0B2AFB2B3 C=B0B5AFB2B0
```