

# CUSTOMER SERVICE BULLETIN

## Radio Shack® CUSTOMER SERVICE BULLETIN

400 Atrium—One Tandy Center, Fort Worth, Texas 76102

<b>Bulletin No.</b>	4831-03
<b>Description</b>	SCRIPSIT-HD
<b>Model</b>	Model II
<b>Stock No.</b>	26-4831 Vers. 01.00.02
<b>Date</b>	April 4, 1983
<b>Page 1 of</b>	1

### Problem

Hyphenation from repaginate will not work. Large gaps will be left in te

\* \* THE FOLLOWING PATCHES ARE REQUIRED! \* \*

### Solution

Apply the following patches to correct the problem.

```
PATCH SCRIPSIT/SYS R=54 B=173 F=60 C=88
PATCH SCRIPSIT/SYS R=54 B=207 F=60 C=88
PATCH SCRIPSIT/SYS R=54 B=237 F=60 C=88
PATCH SCRIPSIT/SYS R=57 B=94 F=60 C=88
PATCH SCRIPSIT/SYS R=43 B=21 F=22CC C=AEDC
PATCH SCRIPSIT/CMD A=DCAE F=20202020202020 C=CD2DB4C0C322CC
```

Apply the following patch to change the version number.

```
PATCH SCRIPSIT A=E2E3 F='2' C='3'
```

After patches from this Bulletin have been applied, the version number will be 01.00.03. Please make the necessary entry in your Version Log.