

CUSTOMER SERVICE BULLETIN

Radio Shack® CUSTOMER SERVICE BULLETIN

400 Atrium—One Tandy Center, Fort Worth, Texas 76102

Bulletin No.	4835-05
Description	SCRIPSIT THLN FLPY & HD
Model	Model II/12
Stock No.	26-4835 Version 03.00.04
Date	April 19, 1984
Page 1 of	1

Problem

During spooling of a merge file print, if the program encounters a disk full condition, unexpected results can occur. During a merge, if Scripsit encounters a single brace ({} no error message is returned. These patches also correct problems encountered with serial printing, line numbering, and forced end of page.

* * THE FOLLOWING PATCHES ARE REQUIRED! * *

Solution

At TRSDOS II READY, type the following PATCHES to the installed SCRIPSIT HARD DISK package. (**NOTE** You will also need to PATCH a BACKUP copy of your master SCRIPSIT FOR THINLINE FLOPPY AND HARD DISK Diskette. Label this copy version 03.00.05 and put it in a safe place.)

```
PATCH SCRIPSIT/SYS R=151 B=248 F=20200E06 C=C338DB00
PATCH SCRIPSIT/CMD A=DB38 F=20202020202020 C=C2272A0E06FD7E16
PATCH SCRIPSIT/CMD A=DB40 F=20202020202020 C=B930014FC3092A
PATCH SCRIPSIT/SYS R=123 B=65 F=ABE4 C=2EDB
PATCH SCRIPSIT/CMD A=DB2E F=2020202020202020 C=CDABE4D8C8E3E1C358E1
PATCH SCRIPSIT/SYS R=123 B=20 F=CD04E3 C=C38BDC
PATCH SCRIPSIT/CMD A=DC8B F=2020202020202020 C=CD04E3C258E1C303E1
PATCH SCRIPSIT/SYS R=160 B=13 F=65 C=6F
PATCH SCRIPSIT/SYS R=160 B=18 F=3E5FCF C=CD63DE
PATCH SCRIPSIT/SYS R=160 B=115 F=020200DE000000 C=3E5FCFC006053E
PATCH SCRIPSIT/SYS R=160 B=122 F=00000000000000 C=5FCFC9020200DE
PATCH SCRIPSIT A=E330 F=34 C=35
```

After the PATCHES from this bulletin have been applied the Version number will be 03.00.05. Please make the necessary entry in your Version Log.